

# AMU TO OUTPUT ASSEMBLY INTERCONNECT

Pin #	FUNCTION	Pin #	FUNCTION	Pin #	FUNCTION
A1	VDC Ground	B1	+24 VDC in	C1	Address Common
A2	SB3 RxC+	B2	SB3 TxD-	C2	SB3 TxD+
A3	SB3 RxC-	B3	SB3 RxD-	C3	SB3 RxD+
A4	ADDR 0	B4	ADDR 1	C4	ADDR 2
A5	SP3 Coil 3+	B5	SP2 Coil 2+	C5	SP1 Coil 1+
A6	SP3 Coil 3-	B6	SP2 Coil 2-	C6	SP1 Coil 1-
A7	SP6 Coil 6+	B7	SP5 Coil 5+	C7	SP4 Coil 4+
A8	SP6 Coil 6-	B8	SP5 Coil 5-	C8	SP4 Coil 4-
A9	SP9 Coil 9+	B9	SP8 Coil 8+	C9	SP7 Coil 7+
A10	SP9 Coil 9-	B10	SP8 Coil 8-	C10	SP7 Coil 7-
A11	SP12 Coil 12+	B11	SP11 Coil 11+	C11	SP10 Coil 10+
A12	SP12 Coil 12-	B12	SP11 Coil 11-	C12	SP10 Coil 10-
A13	SP14 Coil 14+	B13	SP13 Coil 13-	C13	SP13 Coil 13+
A14	SP14 Coil 14-	B14	FU2-1	C14	FU1-1
A15	NA	B15	FU2-2	C15	FU1-2
A16	Sp1 Green FT1 5/6	B16	SP1 Yellow FT1 3/4	C16	SP1 Red FT1 1/2
A17	SP2 Green FT2 5/6	B17	SP2 Yellow FT2 3/4	C17	SP2 Red FT2 1/2
A18	SP3 Green FT3 5/6	B18	SP3 Yellow FT3 3/4	C18	SP3 Red FT3 1/2
A19	SP4 Green FT4 5/6	B19	SP4 Yellow FT4 3/4	C19	SP4 Red FT4 1/2
A20	SP5 Green FT5 5/6	B20	SP5 Yellow FT5 3/4	C20	SP5 Red FT5 1/2
A21	SP6 Green FT6 5/6	B21	SP6 Yellow FT6 3/4	C21	SP6 Red FT6 1/2
A22	SP7 Green FT7 5/6	B22	SP7 Yellow FT7 3/4	C22	SP7 Red FT7 1/2
A23	SP8 Green FT8 5/6	B23	SP8 Yellow FT8 3/4	C23	SP8 Red FT8 1/2
A24	SP9 Green FT9 5/6	B24	SP9 Yellow FT9 3/4	C24	SP9 Red FT9 1/2
A25	SP10Green FT10 5/6	B25	SP10Yellow FT10 3/4	C25	SP10Red FT10 1/2
A26	SP11Green FT11 5/6	B26	SP11Yellow FT11 3/4	C26	SP11Red FT11 1/2
A27	SP12Green FT12 5/6	B27	SP12Yellow FT12 3/4	C27	SP12Red FT12 1/2
A28	SP13Green FT13 5/6	B28	SP13Yellow FT13 3/4	C28	SP13Red FT13 1/2
A29	SP14Green FT14 5/6	B29	SP14Yellow FT14 3/4	C29	SP14Red FT14 1/2
A30	NA	B30	AC+ RAW	C30	AC+ RAW
A31	EQ Ground	B31	NA	C31	NA
A32	NA	B32	AC- RAW	C32	AC- RAW

<b>TITLE:</b>	
<b>AMU TO OUTPUT ASSEMBLY INTERCONNECT</b>	
<b>Rev Date 07-11-03</b>	<b>6-5-29</b>
<b>MAY 8, 2003</b>	